



RSR Sweep Function Generator

Part No. 01FG32

Back to [RSR Sweep Function Generator Model FG32 Main Page](#)

1. GENERAL SPECIFICATIONS:

A: Generator

Frequency: 0.5Hz ~ 3MHz with 5-digit LED display,
Max. resolution 0.001Hz in 6 steps.

Waveform output: Sine, Square, Triangle, Ramp, Positive Pulse
and Negative Pulse; 6 waveforms total.

Stability: 0.1 % ~ 15 minutes after power-on.
0.2% ~ 24hrs after power-on.

B: Counter

Display: 5 digits 0.36" red LED.

Max. Resolution: 0.001Hz.

Display unit: Hz / KHz Automatically controlled by CPU.

C: Common Specification

Limits of operation: 0°C~40°C, 10%~80%R.H.

Storage Environment: -20°C~70°C, 0%~90%R.H.

Power consumption : 25W.

Power source: AC 115V (±10%) 50/60Hz, FUSE:600mA
AC 230V (±10%) 50/60Hz, FUSE:300mA

Ventilation: DC 12V / 100mA Fan.

Dimensions: 275 x 90 x 300mm

Weight: 2.5Kg Net.

Accessory: Power cord, operating manual.

2. RAMP WAVE:

Frequency: 0.5Hz ~ 2.5MHz, 5-digit LED display, Max. resolution
0.001Hz, 6 steps selected by rotary switch.

Symmetry: 80% (Rise wave) to 20% (Fall wave), < 5%, 1Hz ~ 100KHz.

Rise Wave Linearity: < 2%, 1Hz ~ 100KHz.

3. TRIANGLE WAVE:

Frequency: 0.5Hz ~ 3MHz, 5-digit LED display, Max. resolution 0.001Hz

Symmetry: 50% (Rise wave) to 50% (Fall wave), < 2%, 1Hz ~ 100KHz.

4. SINE WAVE:

Frequency: 0.5Hz ~ 3MHz, 5-digit LED display, Max. resolution 0.001Hz.

Distortion: < 2%, 1Hz ~ 100KHz.

Harmonic Ratio: < 30dB, 100KHz ~ 3MHz

Frequency Response: < 0.1dB, up to 100KHz.
< 1dB, 100KHz to 3MHz.

5. SQUARE WAVE:

Frequency: 0.5Hz ~ 3MHz, 5-digit LED display, Max. resolution 0.001Hz.

Symmetry: 50% (Positive half) to 50% (Negative half), < 2%, 1Hz ~ 100KHz

Rise Time: < 60ns.

6. POSITIVE PULSE:

Frequency: 0.5Hz ~ 2.5MHz, 5-digit LED display.

Width: 0.4sec ~ 100ns, continuous adjustment.

Symmetry: 20% to 80%, < 5%, 1Hz ~ 100KHz.

Rise Time: < 60ns.

7. NEGATIVE PULSE:

Frequency: 0.5Hz ~ 2.5MHz, 5-digit LED display, Max. resolution 0.001Hz.

Width: 0.4sec ~ 100ns.

Symmetry: 80% to 20%, < 5%, 1Hz ~ 100KHz.

Fall Time: < 60ns.

8. MAIN OUTPUT:

Output Impedance: 50W, < 2% Accuracy

Max. Output: 20Vp-p (No-load), ± 1 V
10Vp-p (50Ω load) ± 0.5V

Min. Output: 0.1Vp-p (No-load), or 0.05Vp-p (50Ω load)

Attenuator: One -20dB Attenuator, < 2% Accuracy

9. SYNCHRONOUS OUTPUT:

Output Impedance: 500, < 2%, Accuracy.

Output Level: TTL level, > 3Vp-p fixed amplitude.

Fan Out: > 20

Rise Time: < 30nS.

10. VCF INPUT:

Input Voltage: 0 ~ 10V

Input Frequency: DC ~ 1KHz

Input Frequency Variance: 1: 1 to 1: 1000

11. SWEEP SYNCHRONOUS OUTPUT:

Output Impedance: 1KHz, < 2%

Output Waveform: Linear or Log sweep ramp wave.

Output Amplitude: 10Vp-p (No load) or 5Vp-p (1KΩ load)

Output Frequency: 0.2Hz ~ 100Hz continuous adjustment.

12. SWEEP GENERATOR:

Sweep Form: Linear or Log switchable.

Sweep Speed: 5sec ~ 10ms, continuous adjustment.

Sweep Width: 1:1 ~ 1:100

13. COUNTER:

Display: 5 digits, 0.36" red LED display.

Max. Resolution: 0.001Hz

Display unit: Hz / KHz, Auto range.

Time base: 20MHz

Temperature coefficient: < 10ppm / 度

Accuracy: < 0.002%

Power Supply: +5V, 160mA

INTERNAL COUNTER:

Range: Auto range with 4 resolutions, 0.001Hz / 0.01Hz / 0.001KHz /
0.01KHz, Auto control by CPU.

Display: 0.500Hz ~ 3000.0KHz, Auto select by CPU.

Gate time: Variable, 0.25sec ~ 2sec, Auto - setting.

Min. display digits: 4 digits.

EXTERNAL COUNTER:

Max. Input Voltage: < 250Vrms

Input Impedance: 1 MΩ, < 2%

Input Frequency: 0.2Hz ~ 60MHz

Attenuator: *20 (-26dB) Attenuator

Coupling: AC (HF) — For >100KHz frequency.

DC (LF) — With 100KHz filter, for frequency <100KHz

Range: The same as internal counter.

Min. display digits: 4 digits.

Gate Time: 0.25sec ~ 10sec, Auto-setting, depends on the input frequency

Sensitivity: < 30m Vrms (1MHz)