

Light Meter Adaptor

Part No. 01LX02

Back to [Light Meter Adaptor Model LX02](#) Main Page

Range:	3 ranges, 0 - 50,000 Lux.
Output:	<i>Range 1</i> : 0.1 DCmV per Lux. <i>Range 2</i> : 0.1 DCmV per 10 Lux. <i>Range 3</i> : 0.1 DCmV per 100 Lux.
Accuracy:	± (5% + 0.4mV)
Operating Temp. / R.H.:	0 °C to 50 °C (32 °F to 122 °F). Less than 90% RH
Battery:	006P DC 9V battery.
Power Consumption:	Approx. 6 mA
Dimension:	100 x 50 x 25 mm (3.9 x 1.9 x 1.0 inch)
Weight:	158g / 0.33 LB (including battery)
Accessory Included:	Instruction manual 1 PC. Light sensor probe 1 PC
Application:	To match DMM be used as a precision Light METER.

