

GLOBAL SPECIALTIES®

Digital Wattmeter

True RMS Digital 0–20Amp and 0-2000 Wattmeter

Part No. 01WM1522

Back to [Digital Wattmeter](#) Main Page

Global model 1522 Digital Wattmeter is an accurate low cost instrument designed for use in Engineering, Quality Control and Production Test departments to determine the power consumption of equipments operating directly from a standard 115VAC, 60Hz line. Instrument features large LED display.

In addition to power measurement, the wattmeter measures AC (true RMS) voltage and AC (true RMS) current. The Digital Wattmeter is easy to operate. Each measurement function, voltage (V), current (I) or power (W) is selected by a simple pushbutton switch on the front panel. The Digital Wattmeter can be connected to two different loads. The total load current can be up to 20A maximum.

- Measures True RMS voltage
- Measures True RMS current to 20AMPS
- Measures True Power to 1999 watts
- Touch-activated switches
- Large 3.5 digital green LED Display
- Front and rear outlets
- Power over range Indicator
- Rugged case design



SPECIFICATIONS

Line Input Voltage	115VAC/60Hz
Maximum AC Current	20Amp (35Amp peak)
Maximum Power	1999W
Power Factor	0.5 to unity
Accuracy	Volts 0.75% ± 1 digit Amps 1% ± 1 digit Watts 1% ± 2 digits
Resolution	Volts 0.1V Amps 0.01A Watts 1W
Number of Digits	3.5 digits
Display	Green LED 0.56" high
Size	(HxWxD) 155mm x 170mm x 215mm
Weight	2.5Kg (approx)